

RPB

Wireless Panic Button



The RPB is a wireless panic button designed for the **FORCE Series** and **VISION** intruder alarm systems. When pushed for two seconds, the RPB transmits a panic signal to the control panel.

The RPB is a portable means to call for help from anywhere in the home.

PIMA Electronic Systems' portfolio includes a wide selection of hardwired and wireless detectors, sensors and sirens for both security and safety purposes. Our products are developed with uncompromising quality, ease of installation, and operation experience.

PIMA's wireless detectors integrate the FastLink technology, an advanced wireless detection technology using true, 128-bit AES encryption that ensures maximum wireless security.

PIMA's detectors are a perfect solution for the business as well as for the home markets.

The **FORCE Series** and **VISION** alarm systems interface with a wide selection of expanders and peripherals, enabling the customer to expand the system as needed.

Main Features

- Elegant design
- Supplied with a lanyard
- Battery powered with low battery reporting
- Transmission and low battery LED

Technical Specifications

- Transmission:
 - Frequency (MHz):
 - RPB143/243: 433.92
 - RPB187/287: 868.95
 - Output: 10mW
 - Bandwidth: 100KHz
 - Modulation: FM
- One/Two-way
- Range (Free Space, Min.): 100m
- Battery: 1X CR2032, 3V, Lithium
- Battery Life Expectancy: Up to 3 Years (Normal Usage)
- Dimensions: 5.5 X 3.5 X 1.2 cm
- Weight: 50 gr
- CE compliance
- Operating temperature: -10 to +50 °C
- Humidity (max.): 93% R.H., Non-condensing.

Ordering Information

One-way	Two-way
• RPB143: P/N 8833006	• RPB243: P/N 8833206
• RPB187: P/N 8833011	• RPB287: P/N 8833211



For product information
www.pima-alarms.com

All rights reserved © 2021 Pima Electronic Systems Ltd.

Manufactured by:

PIMA Electronic Systems Ltd.

5 Hatzoref Street, Holon 5885633, ISRAEL

Tel: +972.3.6506414 Fax: +972.3.5500442

Email: support@pima-alarms.com

Doc no. SPC-8833006, Revision: 3-2021